

Bell Tapping Code Card

Description:

The bell emergency communications card depicts the knocking codes applicable for communication between the crew of a lost bell and the rescue team. This would typically be

installed on the inside and outside of the bell.

Specifications:

Width: 150mm
Height: 110mm

Order Detail:

Bell Tapping Code Card:	D-BE-001
-------------------------	----------

Bell Emergency Communication	
<i>For use between the crew of a lost bell and rescue divers</i>	
Code	Situation
3-3-3	Communication opening procedure (inside & outside)
1	Yes or affirmative or agreed
3	No or negative or disagreed
2-2	Repeat please
2	Stop
5	Have you got a seal?
6	Stand by to be pulled up
1-2-1-2	Get ready for through water transfer (open your hatch)
2-3-2-3	You will NOT release your ballasts
4-4	Do release your ballast in 30 minutes from now
1-2-3	Do increase your pressure
3-3-3	Communication closing procedure (inside & outside)

Unconscious Diver Recovery Hoist

Description:

The hoist is typically used in the emergency recovery of a diver into the bell. The hoist assembly includes a 10mm rope on a triple block pulley, a bow shackle and a spring snap hook. The rope length can be cut to suit the client's requirement. This product is CE certified under EN

13157 (Machinery Directive) and can be used in conjunction with fall protection when used for human suspension in accordance with LOLER Regulation 5.

Specifications:

Work Length: 30m
Thickness: 10mm
SWL: 200kg

Order Detail:

Unconscious Diver Recovery Hoist:	D-BE-002
-----------------------------------	----------



Bell Battery Pack

Description:

The pack is designed to fit into the 50 Litre cylinder bracket space. It can be easily integrated and can meet the demands of many of today's modern bell requirements. It is fitted with shunt protection, reverse polarity and short circuit diode protection. The battery pack includes, a battery bank and battery charger built into a

certified external pressure vessel.

Specifications:

Length: 1792mm
Dia.: 256mm
Max External Depth Rating: 300msw
Temp Range: 0°C - 52°C
Voltage Supply: 220/110VAC
Voltage Output: 24VDC
Capacity: 75Amp hrs

Order Detail:

Bell Battery Pack - ABS:	D-BE-003
Bell Battery Pack - DNV:	D-BE-004
Bell Battery Pack - General Spares:	D-BE-003-01
Bell Battery Pack - Battery Replacement Set:	D-BE-003-02

